

MMD-300

WIRELESS MAGNETIC CONTACT

Magnetic detector of open doors and windows, representing the "first line of defense". With the **MMD-300**, the alarm system will react to intrusion before the intruder manages to get into the protected area.

Features:

- compatible with **MICRA** alarm module, **PERFECTA 16-WRL**, **PERFECTA 32-WRL**, **PERFECTA 32-WRL LTE**, **PERFECTA-IP 32-WRL**, **PERFECTA-T-32-WRL** and **PERFECTA 64 M** (equipped with **PERFECTA-RF** module) control panels as well as **VERSA-MCU** and **MTX-300** wireless system controllers,
- radio signals from a detector can be retransmitted by **MRU-300**
- two optional reed switch sensors to facilitate selection of installation place,
- input for connecting an external sensor to protect two points (e.g. two sashes of one window) with a single device,
- energy management system to enable many years of operation without having to replace the CR123A lithium battery,
- detection of tamper, e.g. opening enclosure, ripping away from mounting surface
- enclosure color: white

Application:

Perimeter protection of small-size buildings, such as kiosks, summer houses, boutiques, freestanding garages and workshops

Delivery set:

Detector, flush- or surface-mounted magnets, CR123A lithium battery, mounting elements, user manual



TECHNICAL DATA

| | |
|---|---------------------|
| Additional input sensitivity | 312 ms |
| Environmental class | II |
| Enclosure dimensions | 24 x 110 x 27 mm |
| Operating temperature range | -10...+55 °C |
| Standby mode current consumption | 80 µA |
| Max. current consumption | 27 mA |
| Weight | 64 g |
| Maximum humidity | 93 ±3% |
| Operating frequency band | 433,05 ÷ 434,79 MHz |
| Battery | CR123A 3V |
| Battery working time (energy save mode, in years) | Estimated 3 years |

