

MMD-302 BR

WIRELESS MAGNETIC CONTACT

MMD-302 door and window magnetic opening detector is the part of perimeter protection. The device includes the input for rollerblinds detector, which enables the detection of force opening the outdoor rollerblinds equipped with proper sensors. The **MMD-302** allows the security system to respond to intrusion before the intruder will gain access to the protected premises.

- compatible with **MICRA** alarm module, **PERFECTA 16-WRL**, **PERFECTA 32-WRL**, **PERFECTA-IP 32-WRL**, **PERFECTA-T 32-WRL**, **PERFECTA 64 M** (equipped with **PERFECTA-RF** module) control panels as well as **VERSA-MCU** and **MTX-300** wireless system controllers,
- two selectable reed switches to allow many mounting orientations,
- external rollerblinds sensor input,
- battery management to ensure long life for CR123A battery,
- detection of tampering – opening and removal from mounting



TECHNICAL DATA

| | |
|---|---------------------|
| Enclosure dimensions | 24 x 110 x 27 mm |
| Operating temperature range | -10 °C...+55 °C |
| Max. current consumption | 27 mA |
| Weight | 64 g |
| Maximum humidity | 93±3% |
| Operating frequency band | 433,05 ÷ 434,79 MHz |
| Battery | CR123A 3V |
| Standby current consumption | 80 µA |
| Battery working time (energy save mode, in years) | Estimated 3 years |
| Environmental class according to EN50130-5 | II |
| Additional NC input sensitivity | 312 ms |

